



1. Unplug case lid cover from TB5 on controller circuit board.
2. Remove Stop wire from case lid wiring plug
3. Be sure to run remote station wires up through grommets in bottom of controller case before wiring to case lid wiring plug
4. For one remote station, connect stop wire to common on remote three button
5. For more than one remote station run stop wire to next three button common
6. Run new wire from stop of remote station back to case lid cover wiring plug stop connection
7. From case lid cover wiring plug open terminal, run new wire to remote station open
8. From case lid cover wiring plug close terminal, run new wire to remote station close
9. Plug case lid wiring plug back on to TB5 on controller circuit board